

**2. Remove the lid of your computer:**

- Pop the hood of the ][, ][ Plus, //e, and Franklin by pulling up on the cover at the rear edge (the edge farthest from the keyboard) until the two corner fasteners pop apart.
- The IIGS's lid has two fasteners on the sides of the back panel. Push in on the tops of the fasteners with your forefingers while pushing up with your thumbs and heel of your hands on the side of the lid.

**3. Touch the power supply.**

Don't worry, it's safe! This will discharge any static electricity that may be on your body. Static electricity may damage your computer and card. This is a quick and easy safety precaution—don't blow it.

**4. Remove the RamFactor from its anti-static bag.**

Do not touch the gold edge connectors.

**5. Insert the RamFactor's gold edge connector in any expansion slot *except* slot 3.**

- If you have an Enhanced Apple //e and wish to boot from the RamFactor card when a Control-Reset is executed, install the RamFactor in slot 7. If you will be using Pascal 1.3, install the RamFactor in slots 4, 5, or 6. Do not attempt to install the RamFactor card in the auxiliary slot.
- IIGS users can boot from the RamFactor in any slot (except 3 and the Memory Expansion slot) by accessing the Slots option in the Control Panel Menu and setting the Startup option to the correct slot (described in the IIGS Owner's Manual).
- ♦ **Note:** While you can put the RamFactor into slot 4 or slot 5 of the GS, most users access the mouse and the 3.5" drives (respectively) through these ports.

**6. Replace the computer's top cover.**

**Installing RamFactor in a Franklin Ace 2000 series Computer:**

**1. TURN OFF THE COMPUTER'S POWER SWITCH.**

Never install or remove a card while the computer is on. However, you need to leave the computer plugged in throughout the installation to allow the power supply to discharge static electricity from your body.